International Journal for Innovative Engineering and Management Research
PEER REVIEWED OPEN ACCESS INTERNATIONAL JOURNAL
www.ijiemr.org

COPY RIGHT



ELSEVIER SSRN

2023 IJIEMR. Personal use of this material is permitted. Permission from IJIEMR must be obtained for all other uses, in any current or future media, including reprinting/republishing this material for advertising or promotional purposes, creating new collective works, for resale or redistribution to servers or lists, or reuse of any copyrighted component of this work in other works. No Reprint should be done to this paper, all copy right is authenticated to Paper Authors

IJIEMR Transactions, online available on 05th Apr 2023. Link :http://www.ijiemr.org/downloads.php?vol=Volume-12&issue=Issue 04

10.48047/IJIEMR/V12/ISSUE 04/32

Title **THE DEVELOPMENT OF A MODEST MIMO ANTENNA FOR CELLULAR HANDHELD AND 5G IOT APPLICATIONS**

Volume 12, ISSUE 04, Pages: 239-244

Paper Authors

Mr.K.Ramesh Babu, K.Manoja, M.Rupa Sai Sri, M.Angel Vinitha, M.Priyanka

USE THIS BARCODE TO ACCESS YOUR ONLINE PAPER

To Secure Your Paper As Per UGC Guidelines We Are Providing A Electronic Bar Code

International Journal for Innovative Engineering and Management Research
PEER REVIEWED OPEN ACCESS INTERNATIONAL JOURNAL
www.ijiemr.org

The Development of a Modest MIMO Antenna for CellularHandheld and 5G IoT Applications

Mr.K.Ramesh Babu[1], Assistant Professor, Department of ECE,
Vasireddy Venkatadri Institute of Technology, Nambur, Guntur Dt.,
Andhra Pradesh.

K.Manoja[2], **M.Rupa Sai Sri**[3], **M.Angel Vinitha**[4], **M.Priyanka**[5]
2,3,4,5 UG Students, Department of ECE,
Vasireddy Venkatadri Institute of Technology, Nambur, Guntur Dt.,
Andhra Pradesh.
[1]rammi.ramesh50@vvit.net , [2]19BQ1A0471@vvit.net,[3]19BQ1A0499@vvit.net
[4]19BQ1A0493@vvit.net, [5]19BQ1A0480@vvit.net

ABSTRACT:

Today, wireless communications are a necessary component of daily life. The need for speedier wireless systems has grown significantly during the last ten years. High data rates are becoming increasingly necessary to accommodate the wireless industry's expanding feature set industry of communications. Only with a broadened communications network is a 5G revolution feasible. 5G provides the potential for such a new kind of network to connect nearly everyone and anything, including machines, objects, and gadgets. Because of their beneficial characteristics, such as wave propagation and accessible bandwidth, 5G bands are perfect for early implementation. Compared to 4G, 5G has lower latency, which will facilitate cutting-edge applications like AI. A novel small MIMO antenna system prototype for 5G communications and the internet of networks and things have been suggested. The suggested structure, a 5G MIMO antenna, must support the IoT and the 5G band, and its return loss must be less than -10 dB across its operational range. For the full transmission bandwidth, the elements' mutual coupling must be less than - 20dB. Here, mutual coupling is reduced using a variety of techniques. several antenna characteristics, including the reflectivity. The VSWR, Gain, and Directivity must all be acceptable. 5th generation operating bands are the focus of the antenna system. Almost isotropic far fields are required for the radiation patterns in the E and H planes at the centre frequency. Isotropic radiation patterns are required.

Keywords: 5G, IoT, MIMO, E-Field, H-Field, Planar Antennas.

Software Tools: CST

International Journal for Innovative Engineering and Management Research
PEER REVIEWED OPEN ACCESS INTERNATIONAL JOURNAL
www.ijiemr.org

INTRODUCTION

An essential component of current research in mobile Internet of Things (IoT) connectivity is the exponential development in data rates. Much effort has been put into raising data rates and meeting ever-rising standards like 4G, 4G Long Term Evolution (LTE), and 5G. However, data-hungry devices in IoT still need more and more data rates. The Federal Communication Commission (FCC) has currently assigned 5G spectrum in Sub- 6 GHz and mm-wave bands to be utilised to increase data rates for 5G mobile communications. Additionally, by adding more antennas, multiple input multiple-out (MIMO) can improve data rates (channel capacity) even more. In the present era of communication, mobile phones are utilised for much more than only making and receiving phone calls; instead, the variety of uses for mobile devices is growing tremendously every day. To meet these gadgets' enormous data needs, there must be some kind of cutting-edge technology. Fifth Generation (5G) Communication networks, which will replace current wireless communication systems, should be able to overcome issues with existing systems such coverage range, link dependability and latency, and energy efficiency. The fifth generation of wireless communication systems can be supported by massive MIMO technology.

Demand for speedier wireless systems has increased significantly during the last ten years. Increasingly high data rates are needed to accommodate the wireless communication sector's ever-expanding feature set. In this context, the market for portable electronics, particularly cellular handheld mobile phones, is experiencing remarkable expansion. Many methods are suggested to support large data rates. The Multi-Input Multi-Output (MIMO) technology, which uses multiple antenna elements and ports on both ends, have garnered enormous appeal for the 5G wireless communication standard, the next generation of wireless communication, due to its capacity to support extremely high data rates and having improved dependability without utilising additional frequency and bandwidth. Due to the limited space available in applications like portable handheld devices, MIMO requires the use of multiple antenna elements/ports at both ends of the wireless system.

The method of controlling multipath fading in a non-line-of-sight (NLOS) environment is called antenna diversity. Antenna diversity, also known as space diversity or spatial diversity, is one of several wireless diversity schemes that uses two or more antennas to improve the quality and reliability of a wireless link. It also uses pattern/angle diversity (in angle diversity, directional antennas only receive a portion of all scattered energy), polarisation diversity (a technique to reduce the size of MIMO-e), and other techniques. A crucial component of MIMO technology is the

multi-antenna system. The multipath properties of the wireless communication channel have an impact on MIMO wireless systems, but so do the layout and design of the multi antenna system. Many two-and four-port MIMO/diversity antenna designs that exploit spatial diversity may be found in the literature.

Due to the lack of additional room if the number of antenna elements is raised in order to achieve high data rates, spatial diversity, which primarily accomplishes diversity gain depending on the distance of antenna elements from one another, is difficult to implement in portable devices. While though eight port MIMO antenna systems with spatial variety for diversity gain have been documented in the literature, they utilise two-dimensional (2D) antenna geometries that eventually provide either limited bandwidth or omnidirectional radiation patterns with low gains. As a result, in order to achieve diversity gain while facing space restrictions, it is necessary to investigate and apply additional diversity strategies or their combinations.

Design Configuration

The suggested antenna design details are presented in Fig.2, as well as the values of all the parameters considered in this antenna design are depicted in Table II. The ground plane size WgXLg is assumed to be the size of a typical cellular portable device, which is 60 mm 120 mm. The dielectric material for this antenna design is readily available FR4 substrate. The four antenna components are uniformly distributed at each end of the ground plane. In terms of the construction characteristics employed in t his design, the four antenna components are similar. Each antenna component consists of one radiating plate and one feeding plate.The ports and feeding plates are numbered so that ports located along the width of the ground plane are numbered. Because of four antenna elements are similar, we discuss just the characteristics associated to one unit cell, i.e. the antenna element, and these parameters and their values remains constant across the other unit cells, i.e. the antenna elements. The feeding plate is joined to each antenna element having dimensions Wf1h, where h is the feeding plate's height and Wf1 is its width. Every antenna the element features a radiating plate with the dimensions WtXLt.

TABLE-I: Designed Antenna Parameters

Parameter	Value (mm)	Parameter	Value (mm)
Lg	60	SW1	3
Wg	120	SH1	3.5
T	1.5	SL2	18
Wt	14	SW2	3
Lt	32	SH2	3.5
SL1	13	h	3.5

International Journal for Innovative Engineering and Management Research
PEER REVIEWED OPEN ACCESS INTERNATIONAL JOURNAL
www.ijiemr.org



(a)



(b)



(c)

Fig. 2 Four-element, Four-port antenna

a. 3D view
b. Bottom view
c. Front view

Each antenna element has given a feed line by using two slits. The slit1 is of length SL1 and with width of SW1 similarly the slit2 is of length SL2 and width of SW2 and both slits having height of SH1 and SH2. By performing Boolean operation on both slits i.e., slit1+slit2 both slits are combined as single slit which is a feed line. Ports are assigned to each feed line as shown in Fig.2.

Results

Four identical antenna components share a single port, therefore the ports 1 and 3 do have the same reflection coefficient for confirming the simulation findings. Ports 2 and 4 share the same reflection coefficient in a similar manner. As a result, we have solely contrasted the findings of simulation and measurement for the reflection coefficients S11 and S22. as seen in Figure 3. It is clear from Fig. 3 that the minimum bandwidth covered by the ports and S11 - 10 dB which is the reflection coefficient as shown in Fig. 4, and for a good antenna VSWR should be less than 2 as shown in Fig. 5, and efficiency should be greater than 55 based on the materials used, which is achieved as shown in Fig. 6, and we also observed E-Field and H-Field as shown in Fig. 7. We obtained an efficiency of 69.5, which is greater than 55. We designed the antenna at millimetre wave frequencies spanning from 18 to 28 GHz, and the resonant frequency of the designed MIMO antenna was 18.04GHz.

International Journal for Innovative Engineering and Management Research
PEER REVIEWED OPEN ACCESS INTERNATIONAL JOURNAL
www.ijiemr.org



Fig. 3 S-Parameters



Fig. 4 Reflection Coefficient



Fig. 5 Voltage Standing Wave Ratio



Fig. 6 Total Efficiency



Fig. 7 E-Field and H-Field at port-1

Conclusion

In this, we created For 5G IoT and cellular portable applications, a small, low-profile 4-port, 4-element MIMO antenna supporting several mm-wave frequency ranges from 18-28GHz is described. To achieve diversity gain, the antenna ports use polarized, pattern, and spatial diversities. Hence, in order to satisfy 5G aspirations, we created a MIMO antenna employing these higher frequencies. When frequencies grows bandwidth increases so that the channel capacity improves and as we employed numerous antenna components the communication will be quicker when compared to 4G technology. We obtained

S11-10dB and VSWR2, which are both acceptable.

References

[1] https://www.ncbi.nlm.nih.gov/pmc/articles/PMC7284607/

[2] https://www.techsquareatl.com/t he-collection/2020/11/11/1g-to- 5g-the-evolution-of-wireless- connectivity.

[3] https://www.researchgate.net/publication/333672308_Design_a_4G_MIMO_antenna_over_Wireless_ s

[4] https://slideplayer.com/slide/17031461/.

[5] https://www.3ds.com/products-services/simulia/products/cst- studio-suite/.

[6] https://www.slideshare.net/aymenalobaidi/design-and- simulation-microstrip-patch- antenna-using-cst-microwave- studio.

[7] Massive MIMO for 5G. Available online:https://futurenetworks.ieee.org/techfocus/march2017/massivemimo-for-5g(accessed on 25 January 2020)

[8] Massive MIMO Enables Fixed Wireless Access. Available online: http://www.massive-mimo.net(accessed on 25 January 2020).